

ResponseCard RF LCD

ResponseCard RF LCD is the latest version of our ResponseCard keypad, designed so that participants receive visual confirmation of input. The LCD screen displays response selected, channel setting and battery life.

The ResponseCard is the size of a credit card, and provides the features and functionality required to ensure selections are accurate, timely and effortlessly transmitted to the presenter's receiver. Its lightweight and durable enclosure allows it to be easily transported from room to room or around the globe for optimum portability.



Specifications

Enclosure

Dimensions: 3.3" L x 2.1" W x 0.3" H
Weight: 1.0 oz with batteries
Approximately size of a credit card
Durable, rugged case for maximum longevity

User Input:

12 Keys (1/A - 10/J, Ch/Channel, ?)
Answer Key - answers automatically transmitted
Programmable - manually enter new ID number
ResponseCard Programmer compatible

Display:

Participants receive visual confirmation of transmissions on LCD screen, in addition to LED indicator. Successful transmissions are acknowledged via LED with a three second green light signal. Channel setting and battery life are always present on screen.

Power & Power Management:

Two coin cell CR2032 (3.0V) lithium batteries
Deep sleep mode when not in use
Average battery life is six to 12 months

User Identification

Select a channel in less than five seconds, indicating session choice.
Select a channel anytime - even when a session is underway.
Channel selection is stored in nonvolatile memory.
Channel selection is preserved until changed by participant.

RF Technology:

82 channels can be running at once in close proximity.
Fully FCC, CE and Industry Canada certified.
Will not interfere with other technologies.

Range:

200 ft range (400 ft coverage)

Receiver Compatibility

[RF Receiver](#)
[ResponseCard AnyWhere](#)
[LR Receiver](#)

Optional Hardware

ResponseCard Programmer

Key Features

Easily set and identify ResponseCard Device ID's. Identify ResponseCards in a logical numeric order - record them in participant lists for more customized data management.

Mode choice of Auto Increment ID, User Defined, or Factory Default.

[ResponseCard Programmer User Guide](#)