



ResponseCard RF LCD

The ResponseCard RF LCD clicker is designed so that participants receive visual confirmation of input. The LCD screen displays response selected, channel setting and battery life.

The ResponseCard is the size of a credit card, and provides the features and functionality required to ensure selections are accurate, timely and effortlessly transmitted to the presenter's receiver. Its lightweight, rugged and durable enclosure allows it to be easily transported from room to room or around the globe for optimum portability. ResponseCard RF LCD is compatible with TurningPoint assessment software.

ResponseCard RF LCD Specs

Size & Weight	Height: 3.3 inches (83.8 mm) Width: 2.1 inches (53.3 mm) Depth: 0.3 inches (7.6 mm) Weight: 1.0 ounce (28.4 grams)*	
Range	200 ft. range (400 ft. coverage)	
Battery & Power	Two coin cell CR2032 (3.0V) lithium batteries Deep sleep mode when not in use Average battery life is 6 to 12 months	
Input Device Capability	12 Keys (1/A - 10/J, Ch/Channel, ?) Answer Key - answers automatically transmitted Programmable - manually enter new ID number ResponseCard Programmer compatible	
User Identification	Select a channel in less than five seconds, indicating session choice Select a channel anytime - even when a session is underway Channel selection is stored in nonvolatile memory Channel selection is preserved until changed by participant	
Display		
	LCD Viewable Screen Display	Height: 0.4 inches (1.1 mm) Width: 0.6 inches (1.5 mm)
	Indicators:	Response Confirmation Channel setting Battery life
LED Light	Green Light - Response Confirmation (Three seconds) Red Light - Response Unconfirmed	
RF Technology	82 channels can be running at once in close proximity Fully FCC, CE and Industry Canada certified Will not interfere with other technologies	

*Weight is calculated with the addition of two coin cell CR2032 (3.0V) lithium batteries

